



Quality Products. Service Excellence.

## Hard Wired 168 Series



### Features

- Single winding, does not provide isolation, for use where equipment is already isolated and only voltage change is required.
- Flexible world wide applications, 50 or 60 Hz. operation, 115VAC input.
- Output taps @ 85, 95, 105, 110, 115 and 125VAC.
- Ideal for manual line voltage adjustment for electronic equipment or small appliance operation.
- Models 168B, 168C & 168D are CSA certified (209651)
- Connection by flexible leads, 8" minimum length.
- Remember - These units do NOT convert line frequency



| Part No. | Capacity |      | Overall Dimensions |      |      |      | Weight |  |
|----------|----------|------|--------------------|------|------|------|--------|--|
|          | VA       | A    | B                  | C    | D    | E    | Lbs    |  |
| 168B     | 200      | 3.13 | 3.30               | 3.80 | 2.50 | 1.90 | 4.3    |  |
| 168C     | 350      | 3.13 | 4.00               | 3.80 | 2.50 | 2.70 | 6.5    |  |
| 168D     | 500      | 3.75 | 4.00               | 4.60 | 3.00 | 2.80 | 8      |  |
| 168E     | 750      | 3.75 | 4.50               | 4.60 | 3.00 | 3.30 | 10     |  |
| 168F     | 1000     | 3.75 | 5.50               | 4.60 | 3.00 | 4.30 | 14     |  |
| 168H     | 1500     | 4.38 | 6.10               | 5.30 | 3.50 | 4.50 | 20     |  |
| 168J     | 2000     | 4.38 | 6.60               | 5.30 | 3.50 | 5.10 | 23     |  |



Tags: line transformer, autotransformer, voltage change, manual

Data subject to change without notice

© 2023. Hammond Manufacturing Ltd. All rights reserved.