Technical Data Sheet



SP4T Terminated Ramses SMA 18GHz Latching Self-cut-off Auto-reset Indicators 12Vdc BCD TTL Diodes D-sub connector

PAGE 1/2 ISSUE 22-03-22 SERIE : SPnT PART NUMBER : R574492485

RF CHARACTERISTICS

Number of ways : 4

Frequency range : 0 - 18 GHz Impedance : 50 Ohms

Frequency (GHz)	DC - 3	3 - 8	8 - 12.4	12.4 - 18
VSWR max	1,20	1,30	1,40	1,50
Insertion loss max	0.20 dB	0.30 dB	0.40 dB	0.50 dB
Isolation min	80 dB	70 dB	60 dB	60 dB
Average power (*)	240 W	150 W	120 W	100 W

TERMINATION IMPEDANCE : 50 Ohms

TERM. AVG. POWER AT 25° C : 1 W per termination / 3 W total power

ELECTRICAL CHARACTERISTICS

Actuator : LATCHING
Nominal current ** : 640 mA

Actuator voltage (Vcc) : 12V (10.2 to 13V)

Terminals : 25 pins D-SUB male connector

Indicator rating : 1 W / 30 V / 100 mASelf cut-off time : 40 ms < CT < 120 ms

BCD inputs (E) - High level : 3.5 to 5.5 V / 800μA at 5.5 V

- Low level : 0 to 1.5 V / 20μA at 0.8 V

MECHANICAL CHARACTERISTICS

Connectors : SMA female per MIL-C 39012 Life : 2 million cycles per position

Switching Time*** : < 40 ms Construction : Splashproof Weight : < 250 g

ENVIRONMENTAL CHARACTERISTICS

Operating temperature range : -40°C to +85°C
Storage temperature range : -55°C to +85°C

(* Average power at 25°C per RF Path)

(** At 25° C ±10%)

(*** Nominal voltage; 25° C)







IN

SP4T Terminated Ramses SMA 18GHz Latching Self-cut-off Auto-reset Indicators 12Vdc BCD TTL Diodes D-sub connector

PAGE **2/2** ISSUE **22-03-22** SERIE: SPnT PART NUMBER: **R574492485 DRAWING** 6 x M3 depth 4 1.760 **6** Ø 44.70 **BCD TRUTH TABLE** 2 E1 E3 E2 RF continuity Ind. All ports open 0 0 0 (Forced Reset) 1.500 0 $IN \leftrightarrow 1$ D.E 0 Ø 38.10 **6** $IN \leftrightarrow 2$ 0 D.F 0 1 0 1 1 $IN \leftrightarrow 3$ D.G 0 0 $IN \leftrightarrow 4\,$ D.H 25 pins D-SUB male connector 4-40 UNC **LABEL** TOP VIEW **RADIALL®** [2.618 max.] 66.50 max. [2.421 max.] 61.50 max. 1000000000000000 R574492485 0,00,,, [0.303 max.] 7.70 max. 0 - 18 GHz Un: 12V Lot : _ _ _ _ BOTTOM VIEW 2 1 2.244 \emptyset 57 General tolerances: ±0,5 mm [0,02 in] **SCHEMATIC DIAGRAM** Power input RŢN E2 terminals CUT-OFF / FORCED OR AUTOMATIC RESET BCD-TTL DRIVE D∳ Indicator terminals Actuators

This document contains proprietary information and such information shall not be disclosed to any third party for any purpose whatsoever or used for manufacturing purposes without prior written agreement from Radiall. The data defined in this document are given as an indication, in the effort to improve our products; we reserve the right to make any changes judged necessary.

n

RF inputs