


































Fuse accessory selection guide

Fuse family	Size	PCB fuse clip	PCB mount holder	Panel mount holder	In-line fuse holder	Fuse block
 ABC AGC	1/4" x 1 1/4" 6.3 mm x 32 mm	 1Axxxx	 HBH-I HBV-I	 HTB HK HKP	 HMR HGA HTJ	 HRK HHB HFA HHK HHN HFB HHJ S-4000 S-8000
 AGA	1/4" x 5/8"	1Axxxx	-	-	-	-
 AGW	1/4" x 7/8"	1Axxxx	-	-	HRK HHB	-
 AGX	1/4" x 1"	1Axxxx	-	HJL HJM	HRK HHB HHI	3828-1
 AHC(A) ADC	1/4" x 1 1/4" 6.3 mm x 32 mm	1Axxxx	HBH-I HBV-I	HVP	HVI	S-8000
 AMH & AML	55.4 mm x 17.7 mm x 12 mm	-	-	-	-	FMG BSCR101
 AMX(L)	48 mm x 12 mm x 8.5 mm	-	-	-	-	HMX
 ATC	Auto Blade Fuse 19.1 mm x 18.7 mm	1A5600	-	-	HHF- JFCU	-
 ATM	Mini Blade Fuse 10.92 mm x 16.25 mm	1A5778	-	-	HHM	-
 C519	5 mm x 15 mm	1Axxxx	-	-	HHT	-
 C520	5 mm x 15 mm	1Axxxx	-	-	HHT	-
 FNM FNQ	13/32" x 1 1/2" 10 mm x 38 mm	1A3400	-	HP	HEB	BMM603
 FNQ-R KTK-R LP-CC	13/32" x 1 1/2" 10 mm x 38 mm	1A3400	-	HP	-	BCM603
 GBA GLD	1/4" x 1 1/4" 6.3 mm x 32 mm	1Axxxx	-	HLD	-	S-4000 S-8000
 GBB	1/4" x 1 1/4" 6.3 mm x 32 mm	1Axxxx	HBH-I HBV-I	HTB HK HKP	HMR HGA HTJ	HRK HHB HFA HHK HHN HFB HHJ S-4000 S-8000
 GDA GDB GDC	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB HTC	HHT	HTC-15M HTC-5x8M HTC-78M
 GMA GMC GMD	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB HTC	HHT	HTC-15M HTC-5x8M HTC-78M
 KLKE KLM KTK	13/32" x 1 1/2" 10 mm x 38 mm	1A3400	-	HP	HEB	BMM603 EVMFH

Fuse Family	Size	PCB Fuse Clip	PCB Mount Holder	Panel Mount Holder	In-Line Fuse Holder	Fuse Block	
 MDA MDL MDQ	1/4" x 1 1/4" 6.3 mm x 32 mm	1Axxxx	HBH-I HBV-I	HTB HK HKP	HMR HGA HTJ	HRK HHB HFA HHK HHN HFB HFA HHK	S-4000 S-8000
 MDH	1/4" x 1 1/4" 6.3 mm x 32 mm	1Axxxx	HBH-I HBV-I	HTB HK HKP	HMR HGA HTJ	HRK HHB HVI HHK HHN HFB HHJ	S-4000 S-8000
 PCTron	-	-	BK-PCS	-	-	-	
 S500 S501	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-5x8M HTC-78M	
 S505 S506	5 mm x 20 mm	1Axxxx HTC-2xxM	H15 HBH-M HBV-M	HTB	HHT	HTC-15M HTC-5x8M HTC-78M	
 SC-xxA	13/32" x various lengths 1.31" to 2.25"	1A3400	-	HPS-EE HPS-JJ HPS-FF	HEG HEH HEC HEJ	BG3011PQ	
 SFE	1/4" x various lengths (5/8" to 1 7/16")	1Axxxx	-	-	HR/HM	-	
 SR-5 / SR-5F / SR-5H SS-5 / SS-5F / SS-5H	-	-	BK-PCS	-	-	-	
 TDC10/11	1/4" x 1 1/4" 6.3 mm x 32 mm	1Axxxx	HBH-I HBV-I	HTB HK HKP	HMR HGA HTJ	HRK HHB HFA HHK HHN HFB HHJ	S-4000 S-8000
 TDC180 TDC600	1/4" x 1"	1Axxxx	-	HJL HJM	HRK HHB HHI	3828-1	

Tools & resources

- [Webpage](#)
- [Parametric search tool](#)
- [How to select a fuse holder white paper](#)

Eaton
Electronics Division
1000 Eaton Boulevard
Cleveland, OH 44122
United States
www.eaton.com/electronics

© 2023 Eaton
All Rights Reserved
Printed in USA
Publication No. 10575 BU-ELX22190
February 2023



Eaton is a registered trademark.
All other trademarks are property of their respective owners.