

TAA-Compliant SmartPro 120V 2.2kVA 1.6kW Line-Interactive Sine Wave UPS, Tower, Network Card Options, USB, DB9

MODEL NUMBER: SMART2200SLTAA





Description

The SMART2200SLTAA is compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases. 2200VA line-interactive tower UPS system for server, networking and telecommunications equipment. Upright tower form factor. Offers sine wave 120V nominal output in both AC and battery modes. Switches to battery-derived AC output during power failures and extreme voltage variations. Lineinteractive automatic voltage regulation (AVR) provides voltage boost/cut during brownouts/overvoltages to maintain regulated 120V nominal output over an input voltage range of 83-145V. Includes NEMA 5-20P input plug and 7 UPS-supported (6 x 5-15/20R & 1 L5-20R) output receptacles. Network-grade AC surge and noise suppression. Network management interfaces support simultaneous communications via USB port, DB9 serial port and slot for Network Management Card option. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Supports simultaneous detailed monitoring of equipment load levels, self-test data and utility power conditions via all three network interfaces. PowerAlert power management software is available via free download). Three-stage metered current monitoring and battery charge status LEDs. Utility power and voltage regulation, and battery warning LEDs. Audible alarm. Self-test. Field-replaceable, hot-swappable internal batteries. Attractive all-black color scheme. \$250,000 connected equipment insur; (U.S., Canada, and Puerto Rico only).

Features

- · Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases
- SmartPro line-interactive UPS system is ideal for voice, data, medical and industrial networking
 applications
- Line-interactive voltage regulation maintains selectable 120V nominal output during brownouts as low as 83V and overvoltages to 145V
- Enables continuous operation through blackouts, voltage fluctuations and surges
- Line-interactive automatic voltage regulation (AVR) provides 12% and 24% voltage boost during

Highlights

- Federal Trade Agreements Act / TAA Compliant for GSA Schedule purchases
- 2.2kVA / 2200VA line interactive tower UPS; Sine wave output
- 120V nominal output during brownouts to 83 and overvoltages to 145V
- USB, RS232, EPO and slot for optional Network Management Card
- Front panel status LEDs with detailed load and battery capacity display
- NEMA 5-20P input; 6 NEMA 5-15/20R & 1 L5-20R outlets

Package Includes

- SMART2200SLTAA TAA Compliant UPS System
- USB and DB9 Serial cabling
- User manual



brownouts and a 12% voltage cut during overvoltages

- Standard internal battery set offers 13 min. runtime at half load (800W) and 5 min. at full load (1600W)
- Space-saving upright tower format
- Network interfaces support simultaneous communications via built-in USB port, DB9 serial port and slot for Network Management Card option; Compatible with Tripp Lite UPS management card options WEBCARDLX and SNMPWEBCARD
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from tripplite.eaton.com/products/power-alert
- NEMA 5-20P input plug/6 x NEMA 5-15R and 1 x NEMA L5-20R output receptacles
- Front panel LEDs provide current monitoring, voltage regulation, battery charge level, and battery warning information
- UPS ships fully assembled in full compliance with DOT regulations; no time-consuming connection of internal batteries by user required
- \$250,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only)

Specifications

OVERVIEW		
UPC Code	037332152794	
UPS Type	Line-Interactive	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	14.8A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-20P	
Input Circuit Breakers	20A	
UPS Input Cord Length (ft.)	10	
UPS Input Cord Length (m)	3.1	
Recommended Electrical Service	20A 120V	
ОИТРИТ		
Output Capacity (VA)	2200	
Output Capacity (kVA)	2.2	
Output Capacity (Watts)	1600	
Output Capacity (kW)	1.6	
Power Factor	0.73	
Nominal Voltage Details	120v nominal output in battery mode	
Frequency Compatibility	60 Hz	



Output Voltage Regulation (Line Mode) Output Voltage Regulation (Battery Mode) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) Output AC Waveform (Battery Mode) Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles Individually Controllable Load Banks No BATTERY BATTERY BATTERY Rutime Full Load (min.) 5 min. (1600w) Runtime Half Load (min.) 13 min. (800w) Expandable Runtime No DC System Voltage (POC) 48 Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Access Battery Acce			
Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) Pure Sine wave Output AC Waveform (Battery Mode) Pure Sine wave Output AC Waveform (Battery Mode) 110V: 115V: 120V Output Receptacles (6) S-15/20R; (1) L5-20R Individually Controllable Load Banks No BATTERY Rurrime Full Load (min.) 5 min. (1600w) Runrime Full Load (min.) 13 min. (800w) Expandable Runtime No DC System Voltage (VDC) 48 Battery Recharge Rate (Included Batteries) Battery Acess Battery access door Internal UPS Replacement Battery Cartridge Anbsp.ca classa-'productLink' href='/htripplite eaton.com/UPS-Replacement-Battery-Cartridge-Kit-select-Tripp-Lite-Bastery-Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 24% User InternACE, ALERTS & CONTROLS Switches 2 Switches control office power, tablery over, aVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Output Voltage Regulation (Line Mode)	-18% / +8%	
Output AC Waveform (Battery Mode) Pure Sine wave Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles (6) 5-15/20R; (1) L5-20R Individually Controllable Load Banks No BATTERY Runtime Full Load (min.) 5 min. (1600w) Runtime Half Load (min.) 13 min. (800w) Expandable Runtime No DC System Voltage (VDC) 48 Battery Recharge Rate (Included Batter) Battery Access Battery Access Battery Access Battery Access Internal UPS Replacement Battery Carridge Battery Access Internal UPS Replacement Description Hot-swappable. user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltages to 145V Overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Everer Undervoltage Correction Input voltages between 98 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 98 and 108V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control offon power status and alarm-cancel/self-test operation Autoble Alarm Audible alarm indicates power failure and overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570		+/- 5%	
Nominal Output Voltage(s) 110V: 115V: 120V 110V:	Output AC Waveform (AC Mode)	Sine wave	
Output Receptacles (6) 5-15/20R; (1) L5-20R Individually Controllable Load Banks No BATTERY Runtime Full Load (min.)		Pure Sine wave	
Runtime Full Load (min.) 5 min. (1600w)	Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Runtime Full Load (min.) 5 min. (1600w) Runtime Half Load (min.) 13 min. (800w) Expandable Runtime No DC System Voltage (VDC) 48 Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Cartridge-Kit-select-Tripp-Lite-general PS Replacement Battery Battery Acriticge Best-Powerware-Liebert-other-UPS-RBC54*z-RBC54*z-a- Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible alarm indicates power failture and overload conditions 19 LEDs indicator line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level UPS AC Suppression Joule Rating 570	Output Receptacles	(6) 5-15/20R; (1) L5-20R	
Runtime Full Load (min.) 5 min. (1600w) Runtime Half Load (min.) 13 min. (800w) Expandable Runtime No DC System Voltage (VDC) 48 Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery 8 hours from 10% to 90% Battery Access Battery access door Internal UPS Replacement Battery 8 hours from 10% to 90% Battery Replacement Battery 8 hours from 10% to 90% Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible Alarm and be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions UPS AC Suppression UPS AC Suppression Joule Rating 570	Individually Controllable Load Banks	No	
Runtime Half Load (min.) 13 min. (800w) Expandable Runtime No DC System Voltage (VDC) 48 Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Cartridge Best-Powerware-Liebert-other-UPSRBC54*-RBC54-/as- : Battery Replacement Description WOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible Alarm and a status in a status and alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 570 UPS AC Suppression Joule Rating 570	BATTERY		
Expandable Runtime No DC System Voltage (VDC) 48 Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery East-Powerware-Liebert-other-UPSRBC54*->RBC	Runtime Full Load (min.)	5 min. (1600w)	
Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Cartridge Battery Access Battery Access Battery access door Internal UPS Replacement Battery Cartridge Battery Access Battery Access Battery Best-Powerware-Liebert-other-UPS-RBC54*s-RBC54-/a>-8nbsp; Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Runtime Half Load (min.)	13 min. (800w)	
Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Cartridge &hbsp. RBC54	Expandable Runtime	No	
Battery Access Batter	DC System Voltage (VDC)	48	
Internal UPS Replacement Battery Cartridge : RBC54			
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Battery Replacement Description	Hot-swappable, user replaceable batteries	
Overvoltages to 145V Overvoltage Correction Input voltages between 127 and 145 are reduced by 12% Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 96 and 108V are boosted by 12% Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83V to overvoltages to 145V	
Severe Undervoltage Correction Input voltages between 83 and 95V are boosted by 24% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Overvoltage Correction	Input voltages between 127 and 145 are reduced by 12%	
USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Undervoltage Correction	Input voltages between 96 and 108V are boosted by 12%	
Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Severe Undervoltage Correction	Input voltages between 83 and 95V are boosted by 24%	
Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	USER INTERFACE, ALERTS & CONTROLS		
Audible Alarm Audible alarm indicates power failure and overload conditions LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Switches	2 Switches control off/on power status and alarm-cancel/self-test operation	
LED Indicators 9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch	
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 570	Audible Alarm	Audible alarm indicates power failure and overload conditions	
UPS AC Suppression Joule Rating 570	LED Indicators	9 LEDs indicate line power, battery power, AVR, overload and replace battery status - with a 3-LED level meter for load and battery charge level	
	SURGE / NOISE SUPPRESSION		
	UPS AC Suppression Joule Rating	570	
UPS AC Suppression Response Instantaneous	UPS AC Suppression Response Time	Instantaneous	



EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Primary Form Factor	Tower	
Cooling Method	Fan	
Installation Form Factors Supported with Included Accessories	Tower	
Primary UPS Depth (mm)	318	
Primary UPS Height (mm)	267	
Primary UPS Width (mm)	226	
Shipping Dimensions (hwd / in.)	14.50 x 13.75 x 18.00	
Shipping Dimensions (hwd / cm)	36.83 x 34.92 x 45.72	
Shipping Weight (lbs.)	60.00	
Shipping Weight (kg)	27.22	
UPS Housing Material	Steel	
UPS Power Module Dimensions (hwd, cm)	26.67 x 22.61 x 31.75	
UPS Power Module Dimensions (hwd, in.)	10.5 x 8.9 x 12.5	
UPS Power Module Weight (kg)	25.85	
UPS Power Module Weight (lbs.)	57	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	5 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	287	
AC Mode Efficiency Rating (100% Load)	95%	
Battery Mode Heat Dissipation (BTU/Hr) @ Full Load	889	
Audible Noise	Audible Noise < 50 dBA at Front Side 1 Meter	
COMMUNICATIONS		
Network Management Cards	SNMPWEBCARD; WEBCARDLX	
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Communications Cable	USB and DB9 cabling included	



WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Communications Interface	USB; DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface	
LINE / BATTERY TRANSFER		
Transfer Time	2-4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	83	
High Voltage Transfer to Battery Power (Setpoint)	145	
FEATURES & SPECIFICATIONS		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS	
WARRANTY & SUPPORT		
Product Warranty Period (Worldwide)	2-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance	



© 2023 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.