

9200B 300A True RMS AC Mini Clamp Meter

True RMS provides better accuracy when measuring non-sinusoidal or noisy waveforms

Features:

- 4000 count display and simple 2 button operation
- Built-in non-contact AC voltage detector plus flashlight
- Data Hold
- Auto power off
- Low battery indicator
- CAT III 600V safety rating
- Includes wrist strap, 2 x 1.5V AAA batteries and case
- 1 year warranty



Applications:

Typically, when using a multimeter to measure current, you would have to “break the circuit” and place the meter in series with it, so that voltage and current would pass through it. A clamp meter allows you to easily measure current without breaking the circuit by clamping around a single conductor. This saves time and the circuit will not be damaged

Specifications

| | |
|---------------------|--|
| True RMS/Averaging | True RMS |
| Display Counts | 4000 |
| Clamp Size | 1.14" (27mm) |
| Max cable diameter | 300MCM |
| AC Current | 0.01A to 300A |
| ACA Accuracy | ±3% |
| NCV Detector | 90 to 1000VAC (50/60Hz) |
| Safety Category | CAT III 600V |
| Dimensions / Weight | 6 x 2.4 x 1.1 (152 x 60 x 28mm) / 4.7 oz. (134g) |



Ordering Information:

9200B 300A True RMS AC Mini Clamp Meter
9200B-NIST 9200B Including Certificate of Traceability to N.I.S.T.

