

POWER TRANSFORMER Chassis Mount: International Series

VPL28-900

Electrical Specifications (@25C)

- 1. Maximum Power: 25.0VA
- 2. Input Voltage Series: 230VAC @ 50/60Hz, Parallel: 115VAC@ 50/60Hz
- 3. Output Voltage Series1: 28.0V CT@ 0.89A, Parallel2: 14.0V @ 1.79A
- 4. Voltage Regulation: 20% TYP @ full load to no load
- 5. Hipot: 3500VAC between primary to secondary and windings to core.
- 6. Recommended Fuse³:

Series: Littelfuse p/n 313 1.00HXP, 1.A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-1, 1A 250V, ¼ x 1 ¼

Parallel: Littelfuse p/n 313 2.0HXP, 2A 250V, slow blow, ¼ x 1 ¼ or, Cooper Bussmann p/n BK/MDL-2, 2A 250V, ¼ x 1 ¼

Construction:

Dual winding construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements. Shrouds are provided over the connections of the leads to the windings on both primary and secondary coils. Devices are designed with a minimum of 6mm creepage distance between the primary and secondary and are manufactured with a Class B (130°C) insulation system.

Agency Files:

UL File: E65390, UL 5085-1 and 3 (formerly UL1585), Class 2/3 cUL: File E65390, For Canadian Use (CSA 22.2, No.66.1-06 and No.66.3-06) TUV: File R72182067, EN 61558-1:2005+A1, EN61558-2-6:2009. Double Insulated. Non-inherently Short-Circuit-Proof.











Dimensions:				Units: In inches		
Α	В	С	D	Е	F	
1 037	3 250	2 125	2 212	8 00	0 187	

Weight: 1.3 lbs.

Connections4:

Transformer is provided with 8" (203mm) long, 0.25" (6mm) stripped and tinned, stranded 22 AWG, UL 1015 lead wire.

Input: Series – BLK to BLU, Jumper WHT to BRN

Parallel – BLK to BLU, Jumper BLK to BRN and WHT to BLU

Output: Series - RED to GRY, Jumper YEL to VIO

Parallel - RED to GRY, Jumper RED to VIO and YEL to GRY


RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


² Non-Inherently limited. Class 2 not wet, Class 3 wet.


³ Fuse must be used on **secondary** as conditions of acceptability for UL Class2/3 operation.


⁴ Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.











SCHEMATIC

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

Publish Date: April 26, 2023

¹ Non-Inherently limited. Class 3.