Is Now Part of

ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at
www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild_questions@onsemi.com.

FAIRCHILD SEMICONDUCTOR®

September 2006

FDP8860
N-Channel PowerTrench® MOSFET
30V, 80A, 2.5mΩ

Features

- Max $r_{DS(on)}$ = 2.5mΩ at V_{GS} = 10V, I_D = 80A
- Max $r_{DS(on)}$ = 2.9mΩ at V_{GS} = 4.5V, I_D = 80A
- Low Miller Charge
- Low Q_{rr} Body Diode
- UIL Capability (Single Pulse and Repetitive Pulse)
- RoHS Compliant

General Description

This N-Channel MOSFET has been designed specifically to improve the overall efficiency of DC/DC converters using either synchronous or conventional switching PWM controllers. It has been optimized for low gate charge, low $r_{DS(on)}$ and fast switching speed.

Application

- DC - DC Conversion
- Start / Alternator Sytems



TO-220
FDP Series



MOSFET Maximum Ratings T_C = 25°C unless otherwise noted

Symbol	Parameter		Ratings	Units
V_{DS}	Drain to Source Voltage		30	V
V_{GS}	Gate to Source Voltage		±20	V
I_D	Drain Current -Continuous (Package limited)	T_C = 25°C	80	A
	-Continuous (Silicon limited)	T_C = 25°C	219	
	-Pulsed	(Note 1)	556	
E_{AS}	Single Pulse Avalanche Energy	(Note 2)	673	mJ
P_D	Power Dissipation		254	W
T_J, T_{STG}	Operating and Storage Temperature		-55 to +175	°C

Thermal Characteristics

$R_{\theta JC}$	Thermal Resistance, Junction to Case TO220	0.59	°C/W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient TO220	62	

Package Marking and Ordering Information

Device Marking	Device	Package	Reel Size	Tape Width	Quantity
FDP8860	FDP8860	TO220AB	Tube	N/A	50 units

Electrical Characteristics T_J = 25°C unless otherwise noted

Symbol	Parameter	Test Conditions	Min	Typ	Max	Units
Off Characteristics						
BV_{DSS}	Drain to Source Breakdown Voltage	I_D = 1mA, V_{GS} = 0V	30			V
$\frac{\Delta BV_{DSS}}{\Delta T_J}$	Breakdown Voltage Temperature Coefficient	I_D = 1mA, referenced to 25°C		22		mV/°C
I_{DSS}	Zero Gate Voltage Drain Current	V_{DS} = 24V, V_{GS} = 0V			1	μA
		V_{DS} = 24V, V_{GS} = 0V, T_J = 150°C			250	μA
I_{GSS}	Gate to Source Leakage Current	V_{GS} = ±20V			±100	nA
On Characteristics						
$V_{GS(th)}$	Gate to Source Threshold Voltage	V_{GS} = V_{DS}, I_D = 250μA	1	1.6	2.5	V
$\frac{\Delta V_{GS(th)}}{\Delta T_J}$	Gate to Source Threshold Voltage Temperature Coefficient	I_D = 250μA, referenced to 25°C		-9.6		mV/°C
$r_{DS(on)}$	Drain to Source On Resistance	V_{GS} = 10V, I_D = 80A		1.9	2.5	mΩ
		V_{GS} = 5V, I_D = 80A		2.0	2.8	mΩ
		V_{GS} = 4.5V, I_D = 80A		2.1	2.9	mΩ
		V_{GS} = 10V, I_D = 80A, T_J = 150°C		2.9	3.8	mΩ
g_{FS}	Forward Transconductance	V_{DS} = 10V, I_D = 80A		3.4		S
Dynamic Characteristics						
C_{iss}	Input Capacitance	V_{DS} = 15V, V_{GS} = 0V, f = 1MHz		9200	12240	pF
C_{oss}	Output Capacitance			1700	2260	pF
C_{rss}	Reverse Transfer Capacitance			1060	1590	pF
R_g	Gate Resistance	f = 1MHz		1.7		Ω
Switching Characteristics						
$t_{d(on)}$	Turn-On Delay Time	V_{DD} = 15V, I_D = 80A, V_{GS} = 5V, R_{GEN} = 3Ω		35	56	ns
t_r	Rise Time			135	216	ns
$t_{d(off)}$	Turn-Off Delay Time			64	103	ns
t_f	Fall Time			59	95	ns
$Q_{g(TOT)}$	Total Gate Charge at 10V	V_{GS} = 0V to 10V, V_{DD} = 15V, I_D = 80A		158	222	nC
$Q_{g(5)}$	Total Gate Charge at 5V	V_{GS} = 0V to 5V, V_{DD} = 15V, I_D = 80A		81	114	nC
Q_{gs}	Gate to Source Gate Charge	V_{DD} = 15V, I_D = 80A		27		nC
Q_{gd}	Gate to Drain “Miller” Charge	V_{DD} = 15V, I_D = 80A		33		nC
Drain-Source Diode Characteristics						
V_{SD}	Source to Drain Diode Forward Voltage	V_{GS} = 0V, I_S = 80A		0.88	1.25	V
		V_{GS} = 0V, I_S = 40A		0.81	1.2	V
t_{rr}	Reverse Recovery Time	I_F = 80A, di/dt = 100A/μs		60	90	ns
Q_{rr}	Reverse Recovery Charge	I_F = 80A, di/dt = 100A/μs		74	111	nC

Notes:
1: Pulse Test: Pulse Width < 80μs, Duty cycle < 0.5%.
2: Starting T_J =25°C, L= 0.3mH, I_{AS} = 67A,V_{DD} = 27V, V_{GS} = 10V.

Typical Characteristics T_J = 25°C unless otherwise noted



Figure 1. On Region Characteristics



Figure 2. Normalized On-Resistance vs Drain Current and Gate Voltage



Figure 3. Normalized On Resistance vs Junction Temperature



Figure 4. On-Resistance vs Gate to Source Voltage



Figure 5. Transfer Characteristics



Figure 6. Source to Drain Diode Forward Voltage vs Source Current

Typical Characteristics T_J = 25°C unless otherwise noted



Figure 7. Gate Charge Characteristics



Figure 8. Capacitance vs Drain to Source Voltage



Figure 9. Unclamped Inductive Switching Capability



Figure 10. Maximum Continuous Drain Current vs Case Temperature



Figure 11. Forward Bias Safe Operating Area



Figure 12. Single Pulse Maximum Power Dissipation

Typical Characteristics T_J = 25°C unless otherwise noted



Figure 13. Transient Thermal Response Curve

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™	FACT Quiet Series™	OCX™	SILENT SWITCHER®	UniFET™
ActiveArray™	GlobalOptoisolator™	OCXPro™	SMART START™	UltraFET®
Bottomless™	GTO™	OPTOLOGIC®	SPM™	VCX™
Build it Now™	HiSeC™	OPTOPLANAR™	Stealth™	Wire™
CoolFET™	I^2C™	PACMAN™	SuperFET™	
CROSSVOLT™	*i-Lo*™	POP™	SuperSOT™-3	
DOME™	ImpliedDisconnect™	Power247™	SuperSOT™-6	
EcoSPARK™	IntelliMAX™	PowerEdge™	SuperSOT™-8	
E^2CMOS™	ISOPLANAR™	PowerSaver™	SyncFET™	
EnSigna™	LittleFET™	PowerTrench®	TCM™	
FACT™	MICROCOUPLER™	QFET®	TinyBoost™	
FAST®	MicroFET™	QS™	TinyBuck™	
FASTr™	MicroPak™	QT Optoelectronics™	TinyPWM™	
FPS™	MICROWIRE™	Quiet Series™	TinyPower™	
FRFET™	MSX™	RapidConfigure™	TinyLogic®	
	MSXPro™	RapidConnect™	TINYOPTO™	
Across the board. Around the world.™		µSerDes™	TruTranslation™	
The Power Franchise®		ScalarPump™	UHC™	
Programmable Active Droop™				

PRODUCT STATUS DEFINITIONS
Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Rev. I20

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:
Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303−675−2175 or 800−344−3860 Toll Free USA/Canada
Fax: 303−675−2176 or 800−344−3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800−282−9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81−3−5817−1050

ON Semiconductor Website: **www.onsemi.com**

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative