


Corcom | Corcom BCF TE Internal #: 3-1609989-7 3-Phase Filters, 130A Current Rating, Stud Input, Stud Output, DELTA (3 wire + ground), Operating Voltage 480 VAC, Chassis, Corcom BCF

View on TE.com >





Current Rating: 130 A Input Termination Type: Stud Output Termination Type: Stud Wiring Configuration: DELTA (3 wire + ground) Operating Voltage: 480 VAC

All 3 Phase Filters, Corcom BCF Series (36)



Features

Product Type Features

Filtering Requirements	Filtered
Input Termination Type	Stud
Output Termination Type	Stud
Configuration Features	
Wiring Configuration	DELTA (3 wire + ground)
Electrical Characteristics	
Leakage Current (Max) (230VAC, 50Hz)	29.4
Leakage Current (Max) (250VAC, 50Hz)	32 mA
Current Rating	130 A
Operating Voltage	480 VAC
Mechanical Attachment	
Product Mount Type	Chassis

3-1609989-7

3-Phase Filters, 130A Current Rating, Stud Input, Stud Output, DELTA (3 wire + ground), Operating Voltage 480 VAC, Chassis, Corcom BCF



Usage Conditions

Operating Temperature Range

-10 - 40 °C

Product Compliance

For compliance documentation, visit the product page on TE.com>

EU RoHS Directive 2011/65/EU	Compliant
EU ELV Directive 2000/53/EC	Compliant
China RoHS 2 Directive MIIT Order No 32, 2016	No Restricted Materials Above Threshold
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JUNE 2023 (235) Candidate List Declared Against: JAN 2022 (223) Does not contain REACH SVHC
Halogen Content	Low Halogen - Br, Cl, F, I < 900 ppm per homogenous material. Also BFR/CFR/PVC Free
Solder Process Capability	Not applicable for solder process capability

Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulation, the information TE provides on SVHC in articles for this part number is based on the latest European Chemicals Agency (ECHA) 'Guidance on requirements for substances in articles' posted at this URL: https://echa.europa.eu/guidance-documents/guidance-on-reach

Compatible Parts



Also in the Series | Corcom BCF

C For support call+1 800 522 6752

3-1609989-7

3-Phase Filters, 130A Current Rating, Stud Input, Stud Output, DELTA (3 wire + ground), Operating Voltage 480 VAC, Chassis, Corcom BCF





Customers Also Bought







TE Part #1-1393766-9

TE Part #7-1625890-0

Documents

Product Drawings

130BCF6R=F8239F

English

CAD Files

3D PDF

3D

Customer View Model

ENG_CVM_CVM_3-1609989-7_A.2d_dxf.zip

English

Customer View Model

ENG_CVM_CVM_3-1609989-7_A.3d_igs.zip

English

Customer View Model

ENG_CVM_CVM_3-1609989-7_A.3d_stp.zip

English

By downloading the CAD file I accept and agree to the **Terms and Conditions** of use.

& For support call+1 800 522 6752

3-1609989-7

3-Phase Filters, 130A Current Rating, Stud Input, Stud Output, DELTA (3 wire + ground), Operating Voltage 480 VAC, Chassis, Corcom BCF



Datasheets & Catalog Pages Corcom BCFxR Flyer

English