# ANT-868-CW-RH-SMA <

TE Internal #: ANT-868-CW-RH-SMA Whip Antenna, Single Band, LPWAN / LoRaWAN, External Mount, Connector, SMA, Omnidirectional, Single Port, Gain < 0 dBi View on TE.com >



#### Antennas



#### Wireless Application: LoRaWAN, LPWAN, Wi-Fi

Mounting Location: External

Mounting Type: Connector

Antenna Termination: SMA

Antenna Type: Whip

## Features

### Product Type Features

Antenna Termination	SMA
Configuration Features	
Antenna Style	Whip
Mounting Location	External
Antenna Type	Whip
Band Type	Single Band
Port Configuration	Single Port
Electrical Characteristics	
VSWR (Max)	<1.9:1
Impedance	50 Ω
Signal Characteristics	
Frequency Band	868 MHz
Nominal Frequency Range	862 - 870
Peak Gain	< 0 dBi
Body Features	
Product Weight	5.94 g[.20952 oz]
Mechanical Attachment	
Polarization	Linear

## ANT-868-CW-RH-SMA

Whip Antenna, Single Band, LPWAN / LoRaWAN, External Mount, Connector, SMA, Omnidirectional, Single Port, Gain < 0 dBi



Mounting Type	Connector
Dimensions	
Product Width	8.5 mm[.33 in]
Product Length	51 mm[2.01 in]
Product Height	0 mm[0 in]
Operation/Application	
Antenna Environment	Outdoor
Directionality	Omnidirectional
Industry Standards	
Wireless Application	LoRaWAN, LPWAN, Wi-Fi
Primary Application	LoRaWAN, LPWAN
<b>Product Compliance</b> For compliance documentation, visit the product page on TE.com>	
EU RoHS Directive 2011/65/EU	Compliant with Exemptions
EU ELV Directive 2000/53/EC	Not Yet Reviewed

Restricted Materials Above Threshold

#### EU REACH Regulation (EC) No. 1907/2006

China RoHS 2 Directive MIIT Order No 32, 2016

Halogen Content

Solder Process Capability

Product Compliance Disclaimer

Current ECHA Candidate List: JUNE 2023 (235) Not Yet Reviewed

Not Yet Reviewed for halogen content

Not reviewed for solder process capability

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulations, TE's information on SVHC in articles for this part number is still based on the European Chemical Agency (ECHA) 'Guidance on requirements for substances in articles' (Version: 2, April 2011), applying the 0.1% weight on weight concentration threshold at the finished product level. TE is aware of the European Court of Justice ruling of September 10th, 2015 also known as O5A (Once An Article Always An Article) stating that, in case of 'complex object', the threshold for a SVHC must be applied to both the product as a whole and simultaneously to each of the articles forming part of its composition. TE has evaluated this ruling based on the new ECHA "Guidance on requirements for substances in articles" (June 2017, version 4.0) and will be updating its statements accordingly.

## ANT-868-CW-RH-SMA

Whip Antenna, Single Band, LPWAN / LoRaWAN, External Mount, Connector, SMA, Omnidirectional, Single Port, Gain < 0 dBi



## **Compatible Parts**



# Customers Also Bought





TE Part #CSI-SGFB-100-UFFR SMA to U.FL/MHF1 100mm 1.13 OD TE Part #EVM-868-PRC-CAS Eval-Module HUM-PRC 868MHz FHSS XCVR CAS TE Part #HUM-868-PRO-UFL Module HUM-PRO 868MHz FHSS FM XCVR EU



TE Part #MDEV-868-PRC Dev-Kit HUM-PRC 868MHz FHSS Development

## Documents

Product Drawings Antenna 1/4 Wave Short 868MHz SMA

English

Antenna 1/4 Wave Short 868MHz SMA

English

Datasheets & Catalog Pages

**C** For support call+1 800 522 6752

## ANT-868-CW-RH-SMA

Whip Antenna, Single Band, LPWAN / LoRaWAN, External Mount, Connector, SMA, Omnidirectional, Single Port, Gain < 0 dBi



ANT-868-CW-RH

English